# POWER DIVIDER/COMBINER





### R&K-PD160-1S



#### **OUTLINE DRAWING**

**XIN MILLIMETERS** 





■ Frequency Range :5 ~ 1500MHz

■ 8Way-0°

■ Low Cost

■ RoHS Compliance

#### **SPECIFICATIONS**

Frequency Range : 5 - 1500MHz Insertion Loss : 5.5dB (max.)

(Except Theoretical Loss 9.0dB)

Amplitude Balance : 1.0dB (max.)
Isolation : 15dB (min.)
Phase Balance : 15° (max.)

Phase Difference : 0

Between Output Ports

 $\begin{array}{lll} \text{VSWR}(\text{SUM}) & : 1.6:1 \text{ (max.)} \\ \text{VSWR} & : 1.6:1 \text{ (max.)} \\ \text{Impedance} & : 50 \, \Omega \end{array}$ 

Impedance : 50 s2

Maximum RF Input Power
Operating Temperature
Storage Temperature
Connectors (Standard)
Connectors (Option)

Maximum RF Input Power

1 W (1.2:1 Load VSWR)

-40°C to +85°C

SMA-FEMALE

SMA-FEMALE

BNC-FEMALE

125g (typ.)

NOTE: All RF Ports are DC short to GND.


#### **HOW TO ORDER**


Model Name R&K-PD160-1S B = BNC - FEMALE


**SCHEMATIC** 


**%BNC** Operational to 1GHz


#### TYPICAL PERFORMANCE (Temp @+25°C)














R&K reserves the right to make changes in the specifications of or discontinue products at any time without notice. R&K products shall not be used for or in connection with equipment that requires an extremely high level of reliability and safety such as aerospace uses or medical life support equipment. Further, R&K cannot export products to any country for use in military or defense applications.

## **R&K Company Limited**

721-1 Maeda, Fuji-City, Shizuoka-Pref. 416-8577 Japan Tel: +81-545-31-2600 E-mail: info@rkco.jp Fax: +81-545-31-1600 URL: http://rk-microwave.com