POWER DIVIDER/COMBINER




R&K-PD520-0S



OUTLINE DRAWING

XIN MILLIMETERS



■ Frequency Range : 0. 7GHz ~ 2. 7GHz

■ 3way-0°

■ Wilkinson Type

■ Low Cost

■ RoHS Compliance

SPECIFICATIONS @+25°C

Frequency Range : 0.7GHz ~ 2.7GHz Insertion Loss : 0.9dB (max.)

(Except Theoretical Loss 4.8dB)

Amplitude Balance : 0.6dB (max.)
Isolation : 18.0dB (min.)
Phase Balance : 5° (max.)
Phase Difference : 0°

Between Output Ports

 $\begin{array}{lll} \text{VSWR (SUM)} & : 1.5:1 \text{ (max.)} \\ \text{VSWR (Other)} & : 1.4:1 \text{ (max.)} \\ \text{Impedance} & : 50 \, \Omega \end{array}$

Maximum RF Input Power : 5W (1.2:1 Load VSWR)


(Total Combined Power at SUM Port)


Operating Temperature : -40°C to +85°C
Storage Temperature : -40°C to +100°C
Connectors : SMA-FEMALE
Weight : 100g (typ.)


HOW TO ORDER


Model Name R&K-PD520-0S No Option


TYPICAL PERFORMANCE














R&K reserves the right to make changes in the specifications of or discontinue products at any time without notice. R&K products shall not be used for or in connection with equipment that requires an extremely high level of reliability and safety such as aerospace uses or medical life support equipment. Further, R&K cannot export products to any country for use in military or defense applications.

R&K Company Limited

721-1 Maeda, Fuji-City, Shizuoka-Pref.416-8577 Japan Tel:+81-545-31-2600 E-mail:info@rkco.jp Fax:+81-545-31-1600 URL: http://rk-microwave.com